

DESIDERIO, METODI E NUOVI SAPERI

MARATONA INFORMATICA

**SFIDA PROPOSTA DA:
FINCANTIERI**

Industrial BOT 4.0

Creazione di un sistema di monitoraggio per PLC (sistemi ICS) basato su sistema IoT 2040 che permette l'interazione tramite chatbot o comandi vocali. Verifica del traffico per garantire non siano presenti attacchi informatici sui sistemi.

COMPETENZE DI BASE RICHIESTE

Networking, programmazione, scripting, analisi dei dati

COSA VIENE FORNITO

IoT2040, manualistica, switch di rete

COSA OCCORRE PORTARE

Snort o software per analisi di rete, ambienti di sviluppo, QRadar (community edition), Eclipse/NodeRed/NodeJS con SDK Siemens open source per IoT2040. Software SSH, versioni free di Alexa o Google Home, Watson

ALLEGATI/LINK UTILI

SIMATIC IOT2040 – the intelligent gateway for industrial IoT solutions
<https://youtu.be/xtruhSQcxrs>

SIMATIC IOT2020, SIMATIC IOT2040 Manual.

<https://support.industry.siemens.com/cs/ww/en/view/109741658>

SIMATIC IOT2000 SD-Card example image

<https://support.industry.siemens.com/cs/ww/en/view/109741799>

SIMATIC IOT2000 Eclipse Plugin

<https://support.industry.siemens.com/cs/ww/en/view/109744106>

SIMATIC IOT2000 forum

<https://support.industry.siemens.com/tf/ww/en/conf/60/>

IOT2000 Starter Guide and useful information

<https://support.industry.siemens.com/tf/ww/en/posts/iot2000-starter-guide-and-useful-information/155652/?page=0&pageSize=10>

Setting up the SIMATIC IOT2000

<https://support.industry.siemens.com/tf/ww/en/posts/setting-up-the-simatic-iot2000/155642/?page=0&pageSize=10>

Video "How To Set Up A Siemens Simatic IoT2040"

<https://youtu.be/e7Q1Sk9Dk4A>

SFIDA RIVOLTA A CATEGORIE

Senior e Junior


NOTE

La gara è a numero chiuso (saranno ammessi i primi 5 gruppi che si prenoteranno il giorno della sfida). In caso di mancata ammissione, si consiglia di prepararsi in anticipo ad affrontare una delle altre gare disponibili.



Iscrizione
obbligatoria su
www.uniud.it/careercenter

www.uniud.it/conoscenzainfesta





SIEMENS



Setting up • 08/2017

Setting up the SIMATIC IOT2000

SIMATIC IOT2020, SIMATIC IOT2040

Warranty and liability

Note

The Application Examples are not binding and do not claim to be complete regarding the circuits shown, equipping and any eventuality. The Application Examples do not represent customer-specific solutions. They are only intended to provide support for typical applications. You are responsible for ensuring that the described products are used correctly. These Application Examples do not relieve you of the responsibility to use safe practices in application, installation, operation and maintenance. When using these Application Examples, you recognize that we cannot be made liable for any damage/claims beyond the liability clause described. We reserve the right to make changes to these Application Examples at any time without prior notice.

If there are any deviations between the recommendations provided in these Application Examples and other Siemens publications – e.g. Catalogs – the contents of the other documents have priority.

We do not accept any liability for the information contained in this document. Any claims against us – based on whatever legal reason – resulting from the use of the examples, information, programs, engineering and performance data etc., described in this Application Example shall be excluded. Such an exclusion shall not apply in the case of mandatory liability, e.g. under the German Product Liability Act (“Produkthaftungsgesetz”), in case of intent, gross negligence, or injury of life, body or health, guarantee for the quality of a product, fraudulent concealment of a deficiency or breach of a condition which goes to the root of the contract (“wesentliche Vertragspflichten”). The damages for a breach of a substantial contractual obligation are, however, limited to the foreseeable damage, typical for the type of contract, except in the event of intent or gross negligence or injury to life, body or health. The above provisions do not imply a change of the burden of proof to your detriment.

Any form of duplication or distribution of these Application Examples or excerpts hereof is prohibited without the expressed consent of the Siemens AG.

Security information

Siemens provides products and solutions with industrial security functions that support the secure operation of plants, systems, machines and networks. In order to protect plants, systems, machines and networks against cyber threats, it is necessary to implement – and continuously maintain – a holistic, state-of-the-art industrial security concept. Siemens’ products and solutions only form one element of such a concept.

Customer is responsible to prevent unauthorized access to its plants, systems, machines and networks. Systems, machines and components should only be connected to the enterprise network or the internet if and to the extent necessary and with appropriate security measures (e.g. use of firewalls and network segmentation) in place.

Additionally, Siemens’ guidance on appropriate security measures should be taken into account. For more information about industrial security, please visit <http://www.siemens.com/industrialsecurity>.

Siemens’ products and solutions undergo continuous development to make them more secure. Siemens strongly recommends to apply product updates as soon as available and to always use the latest product versions. Use of product versions that are no longer supported, and failure to apply latest updates may increase customer’s exposure to cyber threats.

To stay informed about product updates, subscribe to the Siemens Industrial Security RSS Feed under <http://www.siemens.com/industrialsecurity>.

Table of contents

Warranty and liability	2
1 Task	4
1.1 Overview.....	4
2 Requirements	5
2.1 Required Hardware	5
2.2 Required Software.....	9
3 Operating	10
3.1 Installing the SD-Card Example Image	10
3.2 First Commissioning of the SIMATIC IOT2000.....	15
3.2.1 Remote access with Putty SSH Connection	15
3.2.2 Change IP Address	20
3.2.3 Create new directory on the SIMATIC IOT2000	22
4 Checklist	24
5 Related links	25
6 History	25

1 Task

1.1 Overview

Introduction

This Setting Up shows how to set up the SIMATIC IOT2000 with a SD-Card image provided through the Siemens Industry Online Support.

Goals

After working through this document you know how to

- Get remote access to the SIMATIC IOT2000
- Change the IP-Address of the SIMATIC IOT2000
- Create a new directory on the SIMATIC IOT2000

2 Requirements

2.1 Required Hardware

This chapter contains the hardware required for this Setting up.

SIMATIC IOT2000

Two different versions of the SIMATIC IOT2000 are available. The hardware of both versions is described in this document. However, this Setting Up will only use the SIMATIC IOT2020 as basis for all examples. In order to setup the SIMATIC IOT2040, proceed in the same way as described for the SIMATIC IOT2020.

SIMATIC IOT2020

Hardware Overview:

- Intel Quark® x1000
- 512 MB RAM
- 1 Ethernet Interface
- 1 USB Host Type A
- 1 USB Client microUSB

Figure 2-1




Table 2-1

No.	Description
1	Aperture for wall-mounting
2	Designation for integration of antennas
3	Connection for Power Supply
4	5 LED's, 1 programmable USER LED
5	Left cap
6	Right cap
7	Aperture to lock the right cap
8	RESET button for the CPU
9	USER button
10	Ethernet Interface 10/100 Mbps
11	USB Typ Mini-B
12	USB Typ A

SIMATIC IOT2040

Hardware Overview:

- Intel Quark® x1020
- 1 GB RAM
- 2 Ethernet Interfaces
- 2 RS232/485 interfaces
- Battery buffered RTC

Interface Overview:

Figure 2-2




Table 2-1

No.	Description
1	Aperture for wall-mounting
2	Designation for integration of antennas
3	Connection for Power Supply
4	COM-Interfaces (RS232/485)
5	5 LED's, 1 programmable USER LED
6	Left cap
7	Right cap
8	Aperture to lock the right cap
9	RESET button for the CPU
10	USER button
11	Ethernet Interface 10/100 Mbps
12	Ethernet Interface 10/100 Mbps
13	USB Typ Mini-B
14	USB Typ A

Micro-SD Card

SIMATIC IOT2000 can be operated with a Yocto Linux Operating System, which requires the use of a Micro-SD Card.

The requirement for using SIMATIC IOT2000 with Yocto Linux Operating System is a Micro-SD Card with storage capacity from 8GB up to 32GB.

Engineering Station

To work with the SIMATIC IOT2000 an Engineering Station is required. In this Setting Up a PC with Windows 7 Enterprise is used.

The Engineering Station has to include the following Interfaces:

- SD Card Slot
- Ethernet Port

Ethernet cable

For an Ethernet Connection between the Engineering Station and the SIMATIC IOT2000 in order to establish a SSH connection and to download the Eclipse projects an Ethernet cable is required.

Power supply

In order to run the SIMATIC IOT2000 a power supply is required.

This power supply has to provide between 9 and 36V DC.

2.2 Required Software

This chapter contains the software required for this Setting up.

Micro-SD Card Example Image

To use the full functionality of the SIMATIC IOT2000 a SD-Card Example Image with a Yocto Linux Operating System is necessary to be installed. This Image is provided through the Siemens Industry Online Support.

It can be downloaded [here](#).

PuTTY

To get remote access to the SIMATIC IOT2000 software is required.

In this Getting Started “PuTTY” is used. With this software it is possible to establish a connection to different devices for example via Serial, SSH or Telnet.

The “PuTTY” software can be downloaded [here](#).

Win32 Disk Imager

In order to put the SD Card image to the μ SD Card software is needed.

In this Setting Up the Win32 Disk Imager is used.

The “Win32 Disk Imager” can be downloaded [here](#).

NOTE

All existing data on the SD Card will be removed!

3 Operating

This chapter describes the steps necessary to install and start up the SIMATIC IOT2000 using the hard- and software listed before.


For the necessary software components please refer to the download links in [Chapter 2.2](#)




3.1 Installing the SD-Card Example Image

The first step to work with the SIMATIC IOT2000 is to set up a Micro-SD Card with the Image provided through the [Siemens Industry Online Support](#).




The following table shows the required steps to transfer the SD-Card Image to a Micro-SD Card.


Table 3-1

No.	Action
1.	Insert the μ SD-Card via SD-Card Adapter in the SD-Card Slot of your Engineering Station
2.	Retrieve the downloaded SD Card image .zip-file
3.	Install the downloaded "Win32DiskImager-x.x.x-install.exe"
4.	Start the Win32 Disk Imager
5.	Click on the folder 

No.	Action
6.	<p>Select “*.*” in the right bottom corner Then select the “iot2000-example-image-iot2000.wic” file in the retrieved SD Card Image folder</p> 
7.	<p>Select the drive letter of your SD Card</p> 
8.	<p>Click the “Write” button</p> 

No.	Action
9.	<p>Confirm the warning message NOTE: All data will be deleted</p> 
10.	<p>You will receive a success message if the transfer is done</p> 
11.	<p>Right click on "Safely Remove Hardware and Eject Media"</p>  <p>Choose the SD Card</p>

No.	Action
12.	<p data-bbox="496 309 1358 338">Insert the μSD-Card into the μSD-Card Slot of the SIMATIC IOT2000 as follows:</p> <ol style="list-style-type: none"> <li data-bbox="496 376 786 405">1. Slide the locking down  <p data-bbox="496 931 727 960">2. Open the locking</p>  <ol style="list-style-type: none"> <li data-bbox="496 1496 762 1525">3. Insert the μSD-Card 

No.	Action
	<p data-bbox="496 309 887 338">4. Close the locking and slide it up</p> 

3.2 First Commissioning of the SIMATIC IOT2000

Ethernet cable

The following table shows how to connect the SIMATIC IOT2000 and the engineering station with an Ethernet cable.

Table 3-2

No.	Action
1.	Connect one end of the Ethernet cable to an Ethernet-Port of the Engineering Station
2.	Connect the other end of the Ethernet cable to the Ethernet-Port X1P1 of the SIMATIC IOT2000. Note: If you use the SIMATIC IOT2040 X1P1 is the left port.

Power supply

The following table shows how to connect the SIMATIC IOT2000 to a power supply.

Table 3-3

No.	Action
1.	Power off the power supply
2.	Connect the cable to the connecting terminal
3.	Connect the connecting terminal to the SIMATIC IOT2000
4.	Power on the power supply

CAUTION Only use a DC 9...36V power supply!

3.2.1 Remote access with Putty SSH Connection



The Software “Putty” can be used to get remote access from the Engineering Station to the SIMATIC IOT2000 via Serial, SSH or Telnet.



In this Example the SSH connection is used.



- NOTE** The SIMATIC IOT2000 has a static IP address by default.
This address is **192.168.200.1**.
- The Engineering Station has to be in the same subnet as the SIMATIC IOT2000 to establish a SSH connection!
- NOTE** The first boot may last a few minutes –up to 5 – because the filesystem is resized automatically. The time is depending on the SD card you are using.



The following table shows how to use Putty.

Table 3-4

No.	Action
1.	Open downloaded Putty.exe with double-click 
2.	Configure the connection as follows: <ol style="list-style-type: none"> 1. Choose the Connection Type “SSH” 2. Enter the IP address 192.168.200.1 3. The port is 22 by default 4. This configuration can be saved as Default Settings (Mark Default Settings and press the “Save” Button 

No.	Action
3.	<p>Click on "Open" button for opening the communication to the SIMATIC IOT2000 via SSH.</p> 
4.	<p>Connecting the first time via SSH a Warning dialog will appear. It is necessary to update the SSH key. Press the "Yes" button.</p> 

No.	Action
5.	<p>If once confirmed a login dialog appears</p>  <p>The screenshot shows a PuTTY terminal window titled '192.168.200.1 - PuTTY'. The terminal output is 'login as:' followed by a green cursor. The background is black.</p>
6.	<p>Type "root" and press the Enter key</p>  <p>The screenshot shows the same PuTTY terminal window. The terminal output is 'login as: root' followed by a new line with 'root@iot2000:~#' and a green cursor. The background is black.</p> <p>The login was successful.</p> <p>Note: There is no password set per default.</p>



No.	Action
7.	<p>Set a password for the login “root” because of security issues:</p> <ol style="list-style-type: none"> 1. Type in “passwd” 2. Set a new password (input is hidden) 3. Confirm the password (input is hidden) 
8.	<p>Now a few Linux commands can be tested. For example “cd /” to get in the file system and “ls” to list the folders in the current directory</p> 



3.2.2 Change IP Address

In the default settings of the SIMATIC IOT2000's Image, the IP address is set to **192.168.200.1**. Thus, if another static IP address or a DHCP address is required, this can be set with the `iot2000setup` tool

The following table displays the procedure for configuring the IP address settings.

Table 3-5

No.	Action
1.	Open a valid serial Putty connection and login as root (i.e. See topic 3.3)
2.	Type in " <code>iot2000setup</code> " to open the setup tool, navigate to "Networking" and press "Enter"  A screenshot of a PuTTY terminal window titled "COM5 - PuTTY". The terminal displays the "IOT2000 Setup" menu with the following options: "OS Settings", "Networking" (highlighted in red), "Software", and "Peripherals". A red "Quit" button is visible at the bottom of the menu. At the bottom of the terminal window, there is a navigation instruction: "<Tab>/<Alt-Tab> between elements <Space> selects <F12> next screen".
3.	Go to "Configure Interfaces" and press "Enter"  A screenshot of a PuTTY terminal window titled "COM5 - PuTTY". The terminal displays the "Networking" menu with the following options: "Configure Interfaces" (highlighted in red) and "Back". A red "Back" button is visible below the menu. At the bottom of the terminal window, there is a navigation instruction: "<Tab>/<Alt-Tab> between elements <Space> selects <F12> next screen".

No.	Action
4.	<p>Change the static IP address of your interface here, if required. If a DHCP address is required, write "dhcp" to your interface</p> 
5.	<p>If you want to change the netmask you have to edit the file "interfaces" in the directory "/etc/network" Therefore type in "nano /etc/network/interfaces" and change the netmask for your interface After changing do the following:</p> <ol style="list-style-type: none"> Press Ctrl+X to Exit Press Y to save Press Enter 

NOTE You can use the `iot2000setup` tool for many other settings. Just have a look at it.

3.2.3 Create new directory on the SIMATIC IOT2000


The default storage path for scripts, created with the Eclipse IDE, on the SIMATIC IOT2000 is the directory “tmp”. The files present in this directory, will be automatically deleted after a reset or power failure of the SIMATIC IOT2000.


In order to avoid the loss of scripts, a new directory can be created where the files will be stored.

This is only an example; the projects can be stored in other locations too.

The following table shows how to create a new directory in the SIMATIC IOT2000's filesystem.

Table 3-6

No.	Action
1.	Open a valid serial Putty connection and login as root (i.e. See topic 3.3)
2.	Type in “cd /home” command to change the current directory to the home directory of filesystem, and then press the Enter key.
3.	Type in “mkdir <Foldername>” to create a new directory and then press the Enter key (i.e mkdir ProjectFolder)
	
4.	Type in “ls” to show all directories

No.	Action
	 <pre>192.168.200.1 - PuTTY root@iot2000:/# cd /home root@iot2000:/home# mkdir ProjectFolder root@iot2000:/home# ls ProjectFolder root version root@iot2000:/home#</pre> <p>The created folder is now present in the directory “/home”.</p>

4 Checklist

This chapter contains a Checklist which summarizes all important steps in this Setting up.

Table 4-1

No.	Action
1.	Download the software listed
2.	Write the image to the μSD Card
3.	Insert the μSD-Card to the SIMATIC IOT2000
4.	Connect the Ethernet cable
5.	Connect the Power Supply
6.	Establish a SSH with PuTTY
7.	Change IP-Address
8.	Create a new storage directory for the Eclipse projects

5 Related links

Table 5-1

	Topic
\1\	SIMATIC IOT2000 forum www.siemens.com/iot2000-forum
\2\	Download SD-Card Example Image https://support.industry.siemens.com/cs/ww/en/view/109741799
\3\	SIMATIC IOT2000 Getting Started https://support.industry.siemens.com/tf/ww/en/posts/155643/
\4\	Operating Instructions https://support.industry.siemens.com/cs/document/109741658/simatic-iot2020-simatic-iot2040?dti=0&lc=en-WW

6 History

Table 6-1

Version	Date	Modifications
V1.0	09/2016	First version
V2.0	01/2017	Added chapter "Resize the SD card partition"
V2.1	08/2017	Added iot2000setup tool for changing IP Removed manually resizing of filesystem



SIEMENS
Ingenuity for life

The intelligent gateway for industrial IOT solutions

SIMATIC IOT2040


[siemens.com/iot2000](https://www.siemens.com/iot2000)

With advancing digitalization, there continues to be steady progress in networking between production and office IT. Production data is collected and analyzed in the cloud or in the management system to optimize production. Yet the networking of existing plants represents a major challenge, because equipment from different manufacturers are frequently at different technological levels and often do not speak the same data languages and protocols. A time-consuming and complex retrofitting to connect both worlds soon becomes necessary.


An intelligent gateway that standardizes communication between the various data sources, then analyzes and forwards communications to the corresponding recipients is a solution that can be easily implemented. It makes it possible to implement future-oriented production concepts even for existing plants.

Performance. Openness. Expandability. SIMATIC IOT2040 at a glance

- Various possibilities for programming in high-level languages
- Yocto Linux support
- Easily expandable with Arduino shields and mini PCIe cards
- Compact industrial design and DIN rail mounting
- Energy-saving and high-performance Intel Quark processor and numerous interfaces: Intel Quark x1020 (+Secure Boot), 1 GB RAM, 2 x Ethernet ports, 2 x RS232/485 interfaces, Real Time Clock with battery back-up
- Proven SIMATIC quality with high level of robustness



Sample applications



Preventive maintenance

Collection and analysis of data such as rotational speed and operating time to determine the appropriate maintenance window for a machine based on use.



Optimized shop floor management

Data transmission if there is a shortfall in the minimum inventory of consumables and automatic notification in the shop floor management system to reduce plant downtimes.

Subject to changes and errors. The information given in this document only contains general descriptions and/or performance features which may not always specifically reflect those described, or which may undergo modification in the course of further development of the products. The requested performance features are binding only when they are expressly agreed upon in the concluded contract.

Published by
Siemens AG 2016
Digital Factory
P.O. Box 48 48
90026 Nürnberg, Germany

Article-No. DFFA-B10236-00-7600 PDF
Printed in Germany
Dispo 06303